

文件编号: HY-WIT-1227-F01

文件版本号: NR

ECN NO:

文件名称: OVAL7D-E通道数值表

使用客户:

OVAL7D-E :

DMX channel's functions and their values (8 DMX channels):

Mode/Channel				Value	Function	
4	5	6	8			
1	1	1	1	0-255	Red LED -all arrays : Red (0-Black , 255-100% Red)	LED红色从0~100%
2	2	2	2	0-255	Green LED-all arrays : Green (0-Black , 255-100% Green)	LED绿色从0~100%
3	3	3	3	0-255	Blue LED -all arrays : Blue (0-Black , 255-100% Blue)	LED蓝色从0~100%
4	4	4	4	0-255	White LED -all arrays : White (0-Black , 255-100% White)	LED白色从0~100%
		5	5	0-31 32-63 64-95 96-127 128-159 160-191 192-223 224-255	Shutter, strobe: Led trun off Led turn on Strobe effect slow to fast Led turn on Pulse-effect in sequences Led turn on Random strobe effect slow to fast Led turn on	关闭 打开光 同步频闪从慢到快 打开光 脉冲同步频闪 打开光 异步频闪从慢到快 打开光
	5	6	6	0-255	Dimmer intensity: Intensity 0 to 100%	调光从0到100%
			7	0-10 11-40 41-70 71-100 101-130 131-160 161-190 191-220 221-255	Chasing effect: Led trun off Chase 1 Chase 2 Chase 3 Chase 4 Chase 5 Chase 6 Chase 7 Chase 8	关闭 变化场景1 变化场景2 变化场景3 变化场景4 变化场景5 变化场景6 变化场景7 变化场景8
			8	0-255	Speed chase : Value 0 to 255	速度从慢到快

批准:

审核:

校对:

制定: 邓文平